

Ultra Low Jitter PLL Crystal Oscillator 5.0 x 3.2mm

2.5V/3.3V LVPECL FS XO

NX52SA



Product Features

- 2 selectable output frequencies
- Very low phase jitter < 1.0ps RMS max.
- Wide frequency range 5 \sim 1000MHz
- Thicker crystal for improved reliability
- Low supply current 80mA max.
- Industrial Temperature Range
- Pb-free & RoHS compliant
- Fast lead time

Product Description


The NX52SA XO series is a high performance LVPECL crystal oscillator family with very low jitter performance. Depending on customers' needs, this family devices can support 2 different frequencies using the FS select pin. It supports various options including wider frequency range, 2.5V/3.3V voltage, and various stabilities. It is designed to meet the clock source specifications for communication systems, and other high performance equipment.


Applications


- Networking systems
- Servers and storage systems
- Profession video equipments
- Test and measurement
- FPGA/ASIC clock generation

15-0051

Package: (Scale: none, Dimensions are in mm)








*Extended high frequency power decoupling is recommended (see test circuit for minimum recommendation). To ensure optimal performance, do not route RF traces beneath the package.

Part Ordering Information:



Frequency Select family Specification Code



Pin Functions:

Pin	Function						
1	OE Function						
2	FS						
3	Ground						
4	Q						
5	\overline{Q}						
6	V _{CC}						

Frequency Select Table:

FS	Output
0	Frequency 1*
1	Frequency 2*

*Frequency 1 and Frequency 2 can be any frequencies within the output frequency range.



SaRonix-eCera™ is a Pericom® Semiconductor company • US: +1-408-232-9100 TW: +886-3-4518888

SaRonix-eCera

Ultra Low Jitter PLL Crystal Oscillator 5.0 x 3.2mm

Electrical Performance

Parameter		Min.	Тур.	Max.	Units	Notes	
Output Frequency		5		1000	MHz		
Supply Voltage		3.135	3.3	3.465	V		
		2.375	2.5	2.625			
Supply Current, Output Enabled				80	mA	OE tied to "1" or open	
Supply Current, Out	put Disabled only			40	mA	Output is Hi-Z	
Frequency Stability		±20		±50	ppm	±20ppm is for -20°C to 70°C only	
Operating Temperature Range		-40		+85	°C		
Output Logic 0, V _{OL}				V _{CC} -1.55	V		
Output Logic 1, V _{OH}		V _{CC} -1.2			V		
Output Load		50Ω to V _{CC} -2V output termination					
Duty Cycle		45		55	%	Measured 50% V _{CC}	
Rise and Fall Time				400	ps	Measured 20/80% of waveform	
Jitter, Accumulated , RMS (1-o)				6	ps	20.000 adjacent periods	
Jitter, Phase, RMS	<40MHz		0.4	1	ps	12kHz to 5 MHz frequency band	
	40 to 1000MHz		0.4	1	ps	12kHz to 20 MHz frequency band	
	125MHz, 156.25MHz		0.4	0.6	ps	12kHz to 20 MHz frequency band	
Jitter, pk-pk		40 ps 100,000 random periods		100,000 random periods			

Notes:

1. Stability includes all combinations of operating temperature, load changes, rated input (supply) voltage changes, initial calibration tolerance (25°C), aging (1 year at 25°C average effective ambient temperature), shock and vibration.

2. Phase jitter typical value is depending on output frequencies.

3. For specifications other than those listed, please contact sales.

Output Enable / Disable & Frequency Select Function

Parameter	Min.	Тур.	Max.	Units	Notes
Input Voltage (pin 1 & pin 2), OE & FS	0.7 V _{CC}			V	
Input Voltage (pin 1 & pin 2), OE & FS			0.3 V _{CC}	V	
Output Disable Delay			100	ns	
Output Enable Delay			100	ns	
Settling Time after FS Change			10	ms	
Start up Time			10	ms	

Absolute Maximum Ratings

Parameter	Min.	Тур.	Max.	Units	Notes
Storage Temperature	-55		+125	°C	

For the latest product information visit: http://www.pericom.com/products/crystals-and-crystal-oscillators/hiflex-xo/?part=NX52SA

For test circuit go to: http://www.pericom.com/pdf/sre/tc-pecl-sa.pdf

15-0051

For soldering reflow profile and reliability test ratings go to: <u>http://www.pericom.com/pdf/sre/reflow.pdf</u>

For tape and reel information go to: http://www.pericom.com/pdf/sre/tr 5032 xo.pdf

SaRonix-eCera[™] is a Pericom® Semiconductor company • US: +1-408-232-9100 TW: +886-3-4518888 • www.pericom.co



All specifications are subject to change without notice. NX52SA